

# SINGLE-POINT ELECTRONIC CONTROLLER FOR HEAT TRACING SYSTEMS



#### **PRODUCT OVERVIEW**

The nVent RAYCHEM 460 is a c-UL-us Listed single-point heat tracing controller designed for pipe freeze protection, flow maintenance and heat loss replacement applications. It includes a 5" inch color touch screen display for intuitive set up and programming right out of the box. The 460 controller may be used with line-sensing or ambient-sensing and Proportional Ambient-Sensing Control (PASC) modes. It measures temperatures with two 2 KOhm / 77°F (25°C), 2-wire Thermistor connected directly to the unit. The controller can also measure ground fault current to ensure system integrity. The controller includes ground fault current sensing and relaying equipment compliant with UL1053 standard.

## **FEATURES**

- 5" color touch screen for easy set-up and programming
- · Easy to install push-in cage-clamp wire terminals
- Standalone unit that can be DIN Rail mounted
- Ground fault equipment protection (GFEP) compliant with UL1053
- User-defined settings for ground fault alarm and trip levels
- User-defined high temperature cut-out setting
- · User-defined auto-cycle feature to automatically and regularly test the system for any problems
- Energy efficient PASC mode available
- · Alarm relay for remote alarm annunciation
- Two temperature sensors that can be used for ambient and line sensing
- Programmable in advance in power-off mode by using external power bank/charger and USB connection

# **GENERAL**

Area of use

Non-hazardous locations

Approvals



## **GROUND FAULT PROTECTION**

Built-in GFEP. Heat tracing circuit equipped with the 460 controller do not require additional ground fault protection equipment, simplifying installation and reducing costs. It automatically tests the integrity of the integrated ground fault circuitry, ensuring protection in the event of a ground fault.

## **ELECTRICAL PROPERTIES**

Supply voltage 120/208/240/277 VAC, 50/60 Hz Ambient operating temperature range 32°F (0°C) to 105°F (40°C) Ambient storage temperature range -4°F (-20°C) to 122°F (50°C)

Internal power consumption 9 W maximum

Output relay switching capacity 24 A @ 120/208/240/277 +/-10% Vac; 50/60 Hz

Alarm relay Single pole single throw relay, volt-free; maximum switching capacity (resistive load

only) 1 A/24 VDC, 1 A/24 VAC

Circuit breaker 30 A maximum

Ground fault 30 mA, complies with UL 1053 standard

Real time clock Automatic daylight saving time and leap year correction

Clock accuracy +/-10 minutes per year

Keylock Password protection for parameter settings

USB port For pre-setup in power off mode; for firmware upgrades

## **ENCLOSURE**

Flammability class

Dimensions 210 mm x 90 mm x 85 mm / 8.26" x 3.5" x 3.34"

Ingress protection class TYPE 12 – indoor use only

Enclosure material Polycarbonate


Mounting option Mountable DIN RAIL, 35 mm

Conduit entries Two each-1/2 in conduit entries

Cable gland 3 -hole grommet for temperature sensors maximum cable size

-2 wire: 20 AWG (0,5 mm<sup>2</sup>) DIN EN 60730/VDE 0631-1

## TYPICAL DIMENSIONS AND MODULE LAYOUT



- 1. Touch screen: size 5" resistive
- 2. LED Green: Normal operation, heater on: 1.5 sec on/0.5 sec off

Normal operation, heater off: 1.0 sec on/ 1 sec off

Alarm condition: 0.2 sec on/1.8 sec off

3. M20 Gland: Sensor ambient/sensor pipe/external alarm

## **PROGRAMMING**

Maintain temperature setpoint 32°F (0°C) to 176°F (80°C)

## **SENSOR**

Temperature sensor type

Thermistor 2 KOhm / 77°F (25°C), 2-wire

Sensor tip dimensions

Ø 0.2" (5 mm); length 0.8"(20 mm)

Sensor cable length  $10 \text{ft} (3 \text{ m}) \text{ cable extension up to } 328 \text{ ft} (100 \text{ m}) / 2 \times 16 \text{ AWG}$ 

Sensor temperature range -40°F (-40°C) to 194°F (90°C)

RAYCHEM-DS-H60792-460Controller-EN-2007

## **MONITORING**

Temperature	Low alarm range:	-40°F to 190°F (-40°C to 88°C)	
	High alarm range:	32°F to 190°F (0°C to 88°C)	
Ground fault	Alarm range:	20 - 200 mA	
	Trip range:	20 - 200 mA	
Autocycle	Daily/Weekly/Monthly/Never		
Alarm Relay	The alarm relay is used to provide external alarm for any of the following alarm conditions:		
	1) Ground fault current		
	2) Low system temperature		
	3) High system temperature		
	4) Temperature sensor failure		
	5) Internal error		
	6) Loss of continuity		


7) Loss of incoming supply voltage

Audio (buzzer) and visual alarm (LED light, screen display) for any alarm conditions.

## **MEMORY**

Parameters All parameters are stored in nonvolatile memory, except date and time Clock back-up time 10 days.

## **ELECTRICAL SCHEME**



Size power supply terminals  $3 \times 6 \text{ mm}^2 \text{ maximum/10 AWG}$  Size heating cable terminals  $3 \times 6 \text{ mm}^2 \text{ maximum/10 AWG}$  Size alarm terminals  $3 \times 1,5 \text{ mm}^2 \text{ maximum/16 AWG}$  Size sensor terminal - boiler  $2 \times 1,5 \text{ mm}^2 \text{ maximum/16 AWG}$  Size sensor terminal - pipe  $2 \times 1,5 \text{ mm}^2 \text{ maximum/16 AWG}$ 

## **ORDERING DETAILS**

Description	Catalog	Part Number	Weight
Single-point heat tracing controller for pipe heat tracing systems	460 Controller	P000002338	2.3lbs/1050g
2K NTC Sensor 10 m long	SENSOR-NTC-10M	1244-015847	0.2lbs/90g
Power bank	R-PB-Powersmart	1244-020365	0.33lbs/150g

RAYCHEM-DS-H60792-460Controller-EN-2007

# **North America**

Tel +1.800.545.6258 Fax +1.800.527.5703 thermal.info@nVent.com



Our powerful portfolio of brands:

NVent.com/RAYCHEM CADDY ERICO HOFFMAN RAYCHEM SCHROFF TRACER

HEM-DS-H60792-460Controller-EN-2007